

14 DIGIT COUPLER CODES AAR VERSION 1-29-07
 Current AAR Couplers in Production by Shank Length 1-29-07.pdf

IMPORTANT NOTE: Direct interchangeable replacements must exactly match 14 digit codes listed.

AAR ID	Pattern	Status	Replace with:	AAR Code Number	Supplier	Shank (in)	Comments
E/F Couplers							
EF200E	S611HTE			EFH09B21E2500E	ASF	17.25	
EF201CE	EF210CE			EFK09C00B0500E	NCI	17.25	Slack Reduced
EF202CE	EF202CE			EFH09B00B0J00E	M&T	17.25	Slack Reduced
EF203CE	EF203CE			EFH09T00B050BE	M&T	17.25	Slack Reduced
EF204CE	EF204CE			EFH09B00B0500E	M&T	17.25	Slack Reduced
EF205CE	EF205CE			EFK09B00B0B00E	NCI	17.25	Slack Reduced
EF206CE	EF206CE			EFK09B00B0500E		17.25	Slack Reduced
EF206E	E5318		EF206AE/CE	EFK09B04B2500E	NCI	17.25	
EF207E??	E5314=E5316=EF201E			EFM09C04E1000E	NCI	17.25	Never Made
EF208CE	EF208CE			EFK09B00B050SE	NCI	17.25	Slack Reduced
EF209CE	EF209CE			EFK09B00B050BE	NCI	17.25	Slack Reduced
EF219E				EFH09B02B2500E	BSC	17.25	
EF202E	E4952HTE	Obsolete	EF202CE	EFH09B04B2J00E	M&T	17.25	
EF203E	E4985HTE	Obsolete	EF203CE	EFH09B04B2J00E	M&T	17.25	
EF204E	E4956HTE	Obsolete	EF204CE	EFH09B04B2J00E	M&T	17.25	
EF305CE	EF305CE			EFH18B00B0D00E	M&T	22.00	Slack Reduced
EF306CE	EF306CE			EFH18B00B050BE	M&T	22.00	Slack Reduced
EF307CE	EF307CE			EFH18B00B050SE	M&T	22.00	Slack Reduced
EF305E	E4951HTE	Obsolete	EF305CE	EFH18B05B2D00E	M&T	22.00	
E68DE	E68DE			EFH33B00B0500E	All	31.00	Slack Reduced
SBE68DE	SBE68DE			EFH33B00B050BE	All	31.00	Slack Reduced
SE68DE	SE68DE			EFH33B00B050SE	All	31.00	Slack Reduced
EF502CE	EF502CE			EFH33B00B0510E	M&T	31.00	Slack Reduced
EF504CE	EF504CE			EFH33B00B0E00E	M&T	31.00	Slack Reduced
EF505CE	EF505CE			EFH33B00B0700E	M&T	31.00	Need head lug combination
EF506CE	EF506CE			EFH33B00B0J00E	M&T	31.00	Need head lug combination
EF508E	S646HTE		SBE68BE/CE	EFH33B10B250BE	ASF	31.00	
EF508E	E4986HTE		SBE68BE	EFH33B10B250BE	M&T	31.00	
EF510CE	EF510CE			EFJ33B00B0E00E	M&T	31.00	Slack Reduced
EF511CE	EF511CE			EFJ33B00B050BE	M&T	31.00	Slack Reduced
EF511CE	EF511CE			EFJ33B00B050BE	NCI	31.00	Slack Reduced
EF511E	S644AHTE			EFJ33B10B250BE	ASF	31.00	
EF511E	S644HTE			EFJ33B10B250BE	ASF	31.00	
EF511E				EFJ33B10B250BE	BSC	31.00	
EF512CE	EF512CE			EFJ33B00B0500E	M&T	31.00	Slack Reduced
EF512CE	EF512CE			EFJ33B00B0500E	NCI	31.00	Slack Reduced
EF512E	S592CHTE			EFJ33B10B2500E	ASF	31.00	
EF512E	SE91HTE?			EFJ33B10B2500E	BSC	31.00	
EF518CE	EF518CE			EFH33B00B0510E	NCI	31.00	Slack Reduced

14 DIGIT COUPLER CODES AAR VERSION 1-29-07
 Current AAR Couplers in Production by Shank Length 1-29-07.pdf

IMPORTANT NOTE: Direct interchangeable replacements must exactly match 14 digit codes listed.

AAR ID	Pattern	Status	Replace with:	AAR Code Number	Supplier	Shank (in)	Comments
EF519CE	EF519CE			EFH33B00B0A00E	NCI	31.00	Slack Reduced
EF520CE	EF520CE			EFH33B00B0B00E	NCI	31.00	Slack Reduced
EF520E	E5520		EF520AE/CE	EFK33B10B2B00E	NCI	31.00	
EF521CE	EF521CE			EFH33B00B0E00E	NCI	31.00	Slack Reduced
EF521E	E5526		EF521AE/CE	EFK33B10B2E00E	NCI	31.00	
EF522CE	EF522CE			EFH33B00B0G00E	NCI	31.00	Slack Reduced
EF523CE	EF523CE			EFH33B00B0H00E	NCI	31.00	Slack Reduced
EF527E	E68BHTE			EFH33B10B2500E	BSC	31.00	
EF529E	SE68BHTE			EFH33B10B250SE	BSC	31.00	
EF531E	C50129			EFJ33B00B030BE	M&T	31.00	
EF532CE	EF532CE			EFH33B00B0500E	M&T	31.00	Slack Reduced
EF533CE	EF533CE			EFH33B00B050BE	M&T	31.00	Slack Reduced
EF502E	E4942EHTE	Obsolete	EF502CE	EFH33B05B2510E	M&T	31.00	
EF504E	E4942DHTE	Obsolete	EF504CE	EFH33B10B250BC	M&T	31.00	
EF505E	E4942FHTE	Obsolete	EF505CE	EFH33B10B2H00E	M&T	31.00	
EF506E	E4942FHTE	Obsolete	EF506CE	EFH33B10B2510C	M&T	31.00	
EF510E	E4961HTE	Obsolete	EF510CE	EFJ33B10B2E00E	M&T	31.00	
EF511E	E4979BHTE	Obsolete	EF511CE	EFJ33B10B250BE	M&T	31.00	
EF512E	E4974HTE	Obsolete	EF512CE	EFJ33B10B2500E	M&T	31.00	
EF528CE	EF528CE			EFJ34B00B0500E	M&T	33.00	Slack Reduced
EF528CE	EF528CE			EFJ34B00B0500E	NCI	33.00	Slack Reduced
EF534CE	EF534CE			EFJ34B00B050BE	M&T	33.00	Slack Reduced
EF534CE	EF534CE			EFJ34B00B050BE	NCI	33.00	Slack Reduced
EF601CE	EF601CE			EFJ37B00B0500E	M&T	41.00	Slack Reduced
EF601CE	EF601CE			EFJ37B00B0500E	NCI	41.00	Slack Reduced
EF603CE	EF603CE			EFJ37B00B050BE	M&T	41.00	Slack Reduced
EF604CE	EF604CE			EFJ37B00B050SE	M&T	41.00	Slack Reduced
EF601E	E4984HTE	Obsolete	EF601CE	EFJ37B13E2500E	M&T	41.00	Added 4/5/04
EF60ACE	EF60ACE	Obsolete	EF604CE	EFJ37B00B050SE	M&T	41.00	Slack Reduced
EF60AWE	EF601WE	Obsolete	EF60ACE	EFJ37B00B050SE	M&T	41.00	
EF60BWE	EF60BWE	Obsolete	EF603CE	EFJ37B00B050BE	M&T	41.00	Slack Reduced
E69CE	E69CE			EFJ38B00B0500E	All	48.00	Slack Reduced
SBE69CE	SBE69CE			EFJ38B00B050BE	All	48.00	Slack Reduced
SE69CE	SE69CE			EFJ38B00B050SE	All	48.00	Slack Reduced
EF805CE	EF805CE			EFJ38B00B0520E	M&T	48.00	Slack Reduced
EF806CE	EF806CE			EFL38B00B0500E	M&T	48.00	Slack Reduced
EF807CE	EF807CE			EFJ38B00B0520E	NCI	48.00	Slack Reduced
EF811CE	EF811CE			EFH38B00B0500E	NCI	48.00	Slack Reduced
EF811E	EF811AE			EFH38B00E0500E	NCI	48.00	
EF811E	EF811E		EF811AE	EFH38B13E2500E	NCI	48.00	
EF812E	ASF5			EFH38B13E2500E	ASF	48.00	

14 DIGIT COUPLER CODES AAR VERSION 1-29-07

Current AAR Couplers in Production by Shank Length 1-29-07.pdf

IMPORTANT NOTE: Direct interchangeable replacements must exactly match 14 digit codes listed.

AAR ID	Pattern	Status	Replace with:	AAR Code Number	Supplier	Shank (in)	Comments
EF806E	E4950EHTE	Obsolete	EF806CE	EFL38B14E2500E	M&T	48.00	
EF805E	E4950AHTE	Obsolete	EF805CE	EFJ38B08E2520E	M&T	48.00	

E Couplers

ES205E	S474HTE			ESF04T02C3500E	ASF	16.50	
ES207E	S172HTE			ESG04T01D3500E	ASF	16.50	
EK206E	E4880HTE			EKG10C00A0500E	M&T	17.50	
EK212AE	E1206			EKT10C00A0500E	NCI	17.50	
EK301E	EK301E			EKA16C00A0500E	NCI	21.25	
E60EE	E60EE			EKF17B00A0500E	All	21.50	Slack Reduced
SBE60EE	SBE60EE			EKF17B00A050BE	All	21.50	Slack Reduced
SE60EE	SE60EE			EKF17B00A050SE	All	21.50	Slack Reduced
EK308E	E1343 (EK308E)		E60C	EKF17B02A2500E	NCI	21.50	
EK310E	S615CHTE		SBE60CE/DE	EKF17B02A250BE	ASF	21.50	
EK310E	E4978HTE			EKF17B02A250BE	M&T	21.50	
EK316E	E4983HTE			EKF17D02A2500E		21.50	
EK319E	SE60CHTE			EKF17C02A250SE	BSC	21.50	
EK320E	BE60CE			EKF20B02A3500E		22.50	
E67DE	E67DE			EKK24B00A0500E	All	25.00	Slack Reduced
SBE67DE	SBE67DE			EKK24B00A050BE	All	25.00	Slack Reduced
SE67DE	SE67DE			EKK24B00A050SE	All	25.00	Slack Reduced
EK406E	E4982HTE			EKK24D05A2500E	M&T	25.00	
EK419E	E4988HTE		SBE67CC	EKK24B05A250BE	M&T	25.00	
EK420E	E67BHTE		E67BE/CE	EKK24C05A2500E	ASF	25.00	
EK422E	SE67CHTE			EKK24C05A200SE	BSC	25.00	
EK408E	E1408HT			EKL27B00A0500E	NCI	27.00	
EK411E	EK411E (E1409)			EKL28B10A2500E	NCI	27.50	
EK416E	C8644			EKL28C23A1500E		27.50	
EK417E	E4980HTE			EKM28B19A250BE	M&T	27.50	
ES801E	S529HTE			ESE38B05B2520E	ASF	48.00	
EK801E	EK801E			EKF41B04E2500E	M&T	53.75	
EK801A	EK801AE			EKF41B00E050DE	BSC	n/a	
EK801AE	EK801AE			EKF41B00E050DE	NCI	n/a	

14 DIGIT COUPLER CODES AAR VERSION 1-29-07

Current AAR Couplers in Production by Shank Length 1-29-07.pdf

IMPORTANT NOTE: Direct interchangeable replacements must exactly match 14 digit codes listed.

AAR ID	Pattern	Status	Replace with:	AAR Code Number	Supplier	Shank (in)	Comments
EK801E	ASF8 (S529HTE)			EKF41B04E2500E	ASF	n/a	
EK801E				EKF41B04E2500E	BSC	n/a	
EK802E	ASF12			EKF41B06E2500E	ASF	n/a	

F Couplers

F70DE	F70DE			FFK09B00B000BE	All	17.25	
SF70DE	SF70DE			FFK09B00B000SE	All	17.25	
FF204E	F70CHTE		F70CE/DE	FFK09B04B200BE	ASF	17.25	
FF205AE	F5316			FFK09B04E200BE	NCI	17.25	
FF205E	FF205E			FFK09B04E100BE	NCI	17.25	
FF206E				FFK09B04E200BE	BSC	17.25	
FF211E	F5310			FFM09B04E280BE	NCI	17.25	
FF212AE	FF212AE			FFK09K00B000BE	NCI	17.25	
FF212E	DRESSER2			FFK09K04B200BE	ASF	17.25	
FF213E	SF70CHTE			FFK09B04B200SE	BSC	17.25	
FF214E	F70BHTE		F70CE/DE	FFK09B04B200BE	ASF	17.25	
FF215E	ASF14		F70DE	FFK09B00E000BE	ASF	17.25	
FF217E	S663			FFM09B04B200BE	ASF	17.25	
FF217E				FFM09B04B200BE	BSC	17.25	
FF305E	F612AHTE			FFK39B07B200BE		20.00	
F79DE	F79DE			FFK33B00B060BE	All	31.00	
SF79DE	SF79DE			FFK33B00B060SE	All	31.00	
FF501AE	F5507			FFB33B00B0F0BE	NCI	31.00	
FF501E	S639HTE			FFB33B10B2F0BE	ASF	31.00	
FF501E				FFB33B10B2F0BE	BSC	31.00	
FF507E	F8511HTE			FFK33B10B2F0BE	M&T	31.00	
FF508E	F79CHTE			FFK33B10B2F0BE	BSC	31.00	
FF509E	SF79CHTE			FFK33B10B2F0SE	BSC	31.00	
FF602AE	F5702			FFK37B00B0F0BE	NCI	41.00	
FF604E	F8502HTE			FFK37B13B2F0BE	M&T	41.00	
FF603C	S524BHT	void		FFK37B10B2F0BC	ASF	41.00	
F73EBE	F73EBE			FFK38B00B060BE	All	48.00	
SF73BE	SF73BE			FFK38B00B060SE	All	48.00	
FF802AE	FF802AE (F5804)			FFL38B00B063BE	NCI	48.00	
FF803E	F8501CHTE			FFL38B05E402BE	M&T	48.00	
FF807E	FF807E			FFL41B13E203BE	M&T	60.00	

14 DIGIT COUPLER CODES AAR VERSION 1-29-07

Current AAR Couplers in Production by Shank Length 1-29-07.pdf

IMPORTANT NOTE: Direct interchangeable replacements must exactly match 14 digit codes listed.

AAR ID	Pattern	Status	Replace with:	AAR Code Number	Supplier	Shank (in)	Comments
FF216AE	FF216E			FFJ43B00B000BE	NCI	n/a	
FF216E	FF216E		FF216AE	FFK41B24B200BE	NCI	n/a	
FF402				FFL41D00B061BE	BSC	n/a	
FF807E				FFL__B13E2D3BE	BSC	n/a	
FF807E	FF807E			FFL45B00E203BE	NCI	n/a	
FF808E				FFL42D00B062BE	BSC	n/a	
FF808E	FF808E			FFL45K00B062BE	NCI	n/a	

Rotary Couplers

FR201E	22217HTE			FRA02B16E300BE		15.62	
FR205BE	FR205BE			FRC03R00B000BE	NCI	16.12	Added 4/5/04
FR205E	F9314HTE		FR205E-A	FRC03R16E400BE	NCI	16.12	
FR205E-A	FR205E-A (F9314HTE)			FRC03R16B400BE	NCI	16.12	Corrected 4/5/04
FR206E-A	FR206E-A			FRC03R16E480BE	NCI	16.12	
FR207AE	FR207E			FRD09R00B000BE	NCI	17.25	
FR207E				FRD09R24B200BE	BSC	17.25	
FR207E	FR207E		FR207AE	FRD09R24B200BE	NCI	17.25	
FR208A	FR208AE			RFK09R00B000BE	BSC	17.25	
FR208E				RFK09R02E300BE	BSC	17.25	
FR209E	FR209E			FRD09R00B000BE	M&T	17.25	3 01 Corrected 4/5/04
FV301E	SF12HTE			FVA20B04E200BE	BSC	22.50	
FR304E	S649BHT			FRB00R0000000E	ASF	n/a	